

(19) World Intellectual Property Organization
International Bureau



(43) International Publication Date
9 August 2001 (09.08.2001)

PCT

(10) International Publication Number
WO 01/58218 A1

(51) International Patent Classification⁷: **H05B 33/08**

(NL): MARINUS, Antonius, A., M.; Prof. Holstlaan 6, NL-5656 AA Eindhoven (NL).

(21) International Application Number: **PCT/EP01/00116**

(22) International Filing Date: **8 January 2001 (08.01.2001)**

(74) Agent: **DUSSELDORP, Jan, C.**; Internationaal Octroobureau B.V., Prof Holstlaan 6, NL-5656 AA Eindhoven (NL).

(25) Filing Language: **English**

(81) Designated States (*national*): **CN, JP, KR, MX.**

(26) Publication Language: **English**

(84) Designated States (*regional*): European patent (AT, BE, CH, CY, DE, DK, ES, FI, FR, GB, GR, IE, IT, LU, MC, NL, PT, SE, TR).

(30) Priority Data:
00200370.5 3 February 2000 (03.02.2000) EP

Published:


- with international search report
- before the expiration of the time limit for amending the claims and to be republished in the event of receipt of amendments

(71) Applicant: **KONINKLIJKE PHILIPS ELECTRONICS N.V.** [NL/NL]; Groenewoudseweg 1, NL-5621 BA Eindhoven (NL).

For two-letter codes and other abbreviations, refer to the "Guidance Notes on Codes and Abbreviations" appearing at the beginning of each regular issue of the PCT-Gazette.

(72) Inventors: **JACOBS, Ronny, A., A., M.**; Prof. Holstlaan 6, NL-5656 AA Eindhoven (NL). **HONTELE, Bertrand, J., E.**; Prof. Holstlaan 6, NL-5656 AA Eindhoven

(54) Title: **SUPPLY ASSEMBLY FOR A LED LIGHTING MODULE**



(57) Abstract: A supply assembly for a LED lighting module, comprising a PWM controlled current source supply unit to which the LED lighting module can be connected and a burst control unit which is capable of switching the power supply unit on and off with a burst frequency (fburst) so as to control the mean light output. Preferably, the burst control unit is provided with a pulse duration modulator for controlling the pulse length (T pulse) during which the supply unit is operative.

WO 01/58218 A1

Supply assembly for a LED lighting module

The invention relates to a supply assembly for a LED lighting module, comprising a supply unit to which the LED lighting module can be connected and a burst control unit which is capable of switching the power supply (the voltage or the current) to the LED lighting module on and off with a burst frequency so as to control the mean light output of the LED lighting module.

LED lighting modules are being used more and more to illuminate objects. They are also used as signal lighting, for example in traffic lights. The light output of a LED lighting module can be controlled in various well-known ways. One of said ways consists in controlling (dimming) the current intensity through the module. This has the drawback that at a current intensity below approximately 20% of the nominal current intensity, the relation between the current intensity and the light output becomes largely non-linear, and the efficiency of the module becomes far from optimal. Therefore, solutions have been sought which enable the light intensity to be controlled while the nominal current intensity through the module is maintained. US 5, 661, 645 describes a supply unit for a LED lighting module as described in the opening paragraph. In said document, the burst control unit is arranged between an output of a voltage source and the LED lighting module, so that the power supply to the module with a certain burst frequency can be switched on and off. The voltage source is continuously in the on-state, also when the power supply to the LED lighting module is cut off, which results in an unnecessary loss of energy.

It is an object of the invention to provide an efficient, reliable, inexpensive and simple supply assembly for a LED lighting module with an improved efficacy.

This is achieved in accordance with the invention in that the burst control unit is capable of switching the power supply unit on and off with the burst frequency. In this case, the supply unit is in the on-state only when current is actually being supplied, so that the generation of heat and energy losses are minimized, resulting in an improved efficacy of the system.

Preferably, the burst control unit comprises a pulse-duration modulator which is capable of controlling the length of the pulses during which the supply unit is in the on-state. This enables the mean light output to be controlled.

Preferably, the supply unit is a controlled constant-current source. This has the advantage that further measures in the LED module, such as the provision of additional resistors, are not necessary to control the electric current through the LEDs.

Preferably, the supply unit is a high-frequency switch mode power supply (smmps) which supplies a ripple DC current or a ripple DC voltage, said supply unit preferably comprising a half-bridge converter, a buck converter or a flyback converter. The pulse duration modulator can preferably switch the converter on and off with the burst frequency. In this way, the desired effect can be achieved very efficiently. In addition, preferably the ripple frequency of the converter is an integer multiple of the burst frequency, and the ripple DC voltage or ripple DC current can be synchronized with the burst control signal, resulting in a reduction of any stability problems and loss of energy in the system.

For the same reason, the burst frequency preferably is an integer multiple of the frequency (customarily 50 Hz or 60 Hz) of the voltage source, for example the mains voltage to which the supply assembly can be connected, and the burst control signal is synchronized with the mains voltage signal.

Preferably, the burst frequency lies in the range between 50 and 200 Hz or above 20 kHz; more preferably the burst frequency is 100 Hz (if the mains frequency is 50 Hz) or 120 Hz (if the mains frequency is 60 Hz). When use is made of a half-bridge converter, it is best if the burst frequency is chosen as low as possible in connection with switching losses. However, the frequency should preferably exceed the frequency that can be observed by the human eye (approximately 70 Hz), because at a lower frequency the flicker produced by the LEDs is noticeable, which is annoying. In addition, the frequency should preferably be outside the human range of hearing of 200 Hz to 20 kHz to preclude disturbing sound effects.

Preferably, the current supplied by the supply unit in the on-state to the LED lighting module is a constant current which has been chosen as a nominal current, and which results in an optimum light output of the LED lighting module, so that the supply unit can be optimized for the nominal current intensity, which has a favorable effect on the efficacy.

In a preferred embodiment, the burst control unit is coupled to a sensor which is capable of measuring the temperature and/or the light output of the LED lighting module, said burst control unit being capable of controlling the length of the pulses during which the supply unit is in the on-state in dependence upon the value measured by the sensor. By virtue thereof, the light output of the module can be stabilized under varying conditions. In a further

preferred embodiment, the duration of the pulses can be adjusted by a user. By virtue thereof, the light output of the module can be dimmed in accordance with the user's needs.

The supply assembly as herein disclosed is also suitable to operate a LED lighting module which forms part of a display unit, for instance a liquid crystal display (LCD).

These and other aspects of the invention will be apparent from and elucidated with reference to the embodiments described hereinafter.

In the drawings:

Fig. 1A diagrammatically shows a supply assembly to which a LED lighting module is connected.

Fig. 2 shows a graph wherein the current through the LED lighting module is shown as a function of time.

Fig. 3 shows a first detailed example of the system shown in Figure 1.

Fig. 4 shows a second detailed example of the system shown in Figure 1.

As shown in Fig. 1, a supply assembly I comprises a supply unit, preferably a controlled constant-current source 1, which supplies current to a LED lighting module 2. The LED lighting module 2, for instance as backlight for a LCD comprises a number of light-emitting diodes (LEDs) 3, which may be parallel-connected or series-connected. The figure diagrammatically shows that a burst control unit 4 is capable of switching the controlled constant-current source 1 on and off. For this purpose, the burst control unit 4 emits a burst control signal 5 which is composed of pulses having a duration T_{pulse} which switch on the controlled constant-current source 1 with a burst frequency f_{burst} , as shown in Figure 2. The burst frequency f_{burst} should exceed the frequency that can be observed by the human eye (approximately 70 Hz) because at a lower frequency the flicker produced by the LED lighting module would be very disturbing (cf the monitor of a display tube). However, the burst frequency f_{burst} should not exceed a certain value because this would lead to an unnecessary amount of switching losses and, in addition, might cause undesirable, audible background noises.

In this example, the controlled constant-current source 1 is a high-frequency switch mode power supply (smmps) comprising a half-bridge converter, which half-bridge

converter can be switched on and off by the burst control unit. Other high-frequency converters, such as a buck converter, a flyback converter and other types of converters can also suitably be used as a controlled constant-current source. Such a known controlled constant-current source delivers direct current, the current intensity and/or the voltage of which can be controlled. The distinctive feature of such a controlled constant-current source is that the direct current is a ripple direct current, which means that the current intensity varies with a high ripple frequency between a minimum value 6 and a maximum value 7. The mean of this minimum value 6 and maximum value 7 is the mean direct-current intensity 8 of the controlled constant-current source 1. This current intensity 8 is preferably equal to the current chosen as the nominal current for the LED lighting module 2. The ripple signal of the controlled constant-current source 1 is preferably synchronized with the burst control signal in order to preclude additional switching losses.

Figure 2 shows the situation wherein the mean size of the current 9 through the LED lighting module 2 is set at 50% of the mean current 8 of the controlled constant-current source. This is achieved by setting the pulse duration T_{pulse} at 50% of the cycle length (f_{burst}). By varying the pulse duration T_{pulse} , the mean size of the current 9 through the LED lighting module 2 can obtain any desired value between 0% and 100% of the nominal current delivered by the controlled constant-current source 1. To this end the burst control unit 4 is provided with a pulse duration modulator.

Figures 3 and 4 show preferred embodiments of a supply assembly I, the supply assembly I as shown in Figure 3 being connectable to an AC voltage source, such as the mains, and the supply assembly I as shown in Figure 4 being connectable to a DC voltage source, such as a battery. In common with Figure 1, the high-frequency switch mode power supply shown in Figures 3 and 4 comprises a controlled constant-current source (Switch mode current source) 1, the LED lighting module (LED MODULE) 2 and the burst control unit (Burst control) 4.

The burst control unit 4 may be connected to a dimming device (Dim interface) 14 which can be set by a user via a bus (Bus). The dimming device is capable of controlling the pulse duration (also referred to as pulse width) T_{pulse} of the burst control unit 4 by means of a voltage signal (V_{dim}).

As the light output of LEDs is temperature-dependent, the LED lighting unit 2 may be provided with sensors which observe the temperature ($TEMP_OUT$) and/or the light output (OPT_OUT) of the LED lighting unit 2. The sensors can send a voltage signal (V_{TF} and V_{OF} , respectively) to the burst control unit 4, said voltage signals also being capable of

controlling the pulse duration T_{pulse} . By means of this feedback the light output of the LED lighting module 2 can be efficiently stabilized.

In accordance with Figure 3, the controlled constant-current source 1 is fed, in a manner which is known per se, by a filter/rectifier (Filter/rect.) 10 and a preconditioning device (Preconditioner) 11, which are connected to, for example, a grounded electric mains (110V/60Hz or 230V/50Hz) with terminals L, N and PE. In the case of low-power systems (< 25W), the preconditioning device can be replaced by a simple energy buffer. To preclude any problems regarding the stability of the preconditioning device, it is important to synchronize the burst control signal with the mains voltage signal by means of a synchronization signal (Sync). Auxiliary supply (Aux. supply) 15 provides the different parts of the system with the necessary low-voltage supply.

In accordance with Figure 4, the controlled constant-current source 1 is fed by a DC filter (Filter) 12, and optionally a DC/DC converter (DC-DC converter) 13, which are connected to a storage cell or a battery having terminals L and N.

CLAIMS:

1. A supply assembly for a LED lighting module, comprising a supply unit to which the LED lighting module can be connected and a burst control unit which is capable of switching the power supply to the LED lighting module on and off with a burst frequency (fburst) so as to control the mean light output of the LED lighting module, characterized in that the burst control unit is capable of switching the supply unit on and off with the burst frequency (fburst).
2. A supply assembly as claimed in claim 1, characterized in that the burst control unit comprises a pulse-duration modulator which is capable of controlling the length (Tpulse) of the pulses during which the supply unit is in the on-state.
3. A supply assembly as claimed in claim 1 or 2, characterized in that the supply unit is a controlled constant-current source.
4. A supply assembly as claimed in claim 1, 2 or 3, characterized in that the supply unit is a high-frequency switch mode power supply which supplies a ripple DC current or a ripple DC voltage.
5. A supply assembly as claimed in claim 4, characterized in that the pulse duration modulator can switch the converter on and off with the burst frequency (fburst).
6. A supply assembly as claimed in claim 4 or 5, characterized in that the ripple frequency of the converter is an integer multiple of the burst frequency (fburst), and the ripple DC voltage or ripple DC current can be synchronized with the burst control signal.
7. A supply assembly as claimed in any one of the preceding claims, characterized in that the burst frequency (fburst) is an integer multiple of the frequency of the mains voltage to which the supply assembly can be connected, and the burst control signal can be synchronized with the mains voltage signal.

8. A supply assembly as claimed in any one of the preceding claims, characterized in that the burst frequency (fburst) lies in the range between 50 and 200 Hz or above 20 kHz.

5

9. A supply assembly as claimed in any one of the preceding claims, characterized in that the burst frequency (fburst) is 100 or 120 Hz.

10. A supply assembly as claimed in any one of the preceding claims, characterized in that the current (ILED) supplied by the supply unit in the on-state to the LED lighting module is a constant current which has been chosen as a nominal current, and which results in an optimum light output of the LED lighting module.

1/2




FIG. 1




FIG. 2

2/2




FIG. 3




FIG. 4

INTERNATIONAL SEARCH REPORT

Int onal Application No

PCT/EP 01/00116

A. CLASSIFICATION OF SUBJECT MATTER
IPC 7 H05B33/08

According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)

IPC 7 H05B

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Electronic data base consulted during the international search (name of data base and, where practical, search terms used)

EPO-Internal

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category *	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
X	US 5 912 568 A (KILEY DAVID A) 15 June 1999 (1999-06-15) abstract; figures column 2, line 13 - line 35 column 3, line 16 - line 57 column 4, line 37 - line 64 claims 1-4	1-6, 10
X	DE 197 32 828 A (SIEMENS AG) 4 February 1999 (1999-02-04) the whole document	1-6
A	EP 0 567 280 A (HUGHES AIRCRAFT CO) 27 October 1993 (1993-10-27) abstract; figures column 4, line 17 - line 33 claims 1,5	1-4

☐ Further documents are listed in the continuation of box C.

☒ Patent family members are listed in annex.

* Special categories of cited documents:

"A" document defining the general state of the art which is not considered to be of particular relevance

"E" earlier document but published on or after the international filing date

"I" document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)

"O" document referring to an oral disclosure, use, exhibition or other means

"P" document published prior to the international filing date but later than the priority date claimed

"T" later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention

"X" document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone

"Y" document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art

"&" document member of the same patent family

Date of the actual completion of the international search

21 May 2001

Date of mailing of the international search report

31/05/2001

Name and mailing address of the ISA

European Patent Office, P.B. 5818 Patentlaan 2
NL - 2280 HV Rijswijk
Tel (+31-70) 340-2040, Tx. 31 651 epo nl,
Fax (+31-70) 340-3016

Authorized officer

Maicas, J.

INTERNATIONAL SEARCH REPORT
Information on patent family members

Int onal Application No
PCT/EP 01/00116

Patent document cited in search report		Publication date	Patent family member(s)	Publication date
US 5912568	A	15-06-1999	NONE	
DE 19732828	A	04-02-1999	NONE	
EP 0567280	A	27-10-1993	US 5287372 A	15-02-1994
			CA 2093959 A,C	25-10-1993
			DE 69311838 D	07-08-1997
			DE 69311838 T	02-01-1998
			ES 2103430 T	16-09-1997
			JP 2577179 B	29-01-1997
			JP 6029575 A	04-02-1994
			KR 9616179 B	04-12-1996

**This Page is Inserted by IFW Indexing and Scanning
Operations and is not part of the Official Record**

BEST AVAILABLE IMAGES

Defective images within this document are accurate representations of the original documents submitted by the applicant.

Defects in the images include but are not limited to the items checked:

☒ **BLACK BORDERS**

☐ **IMAGE CUT OFF AT TOP, BOTTOM OR SIDES**

☐ **FADED TEXT OR DRAWING**

☐ **BLURRED OR ILLEGIBLE TEXT OR DRAWING**

☐ **SKEWED/SLANTED IMAGES**

☐ **COLOR OR BLACK AND WHITE PHOTOGRAPHS**

☐ **GRAY SCALE DOCUMENTS**

☒ **LINES OR MARKS ON ORIGINAL DOCUMENT**

☐ **REFERENCE(S) OR EXHIBIT(S) SUBMITTED ARE POOR QUALITY**

☐ **OTHER:** _____

IMAGES ARE BEST AVAILABLE COPY.

As rescanning these documents will not correct the image problems checked, please do not report these problems to the IFW Image Problem Mailbox.